

Casambi Constant Current
 Bluetooth Dimmable
 260-700mA
 <25W

260-700mA
CC

20
IP

Bluetooth
dim

- Independent Dimmable Constant Current LED Driver
- "Flicker-free", PstLM ≤1.0; SVM ≤0.4
- Dimming Range: 2...100%
- Configurable Constant Current Output via Dip-switch
- Open Circuit, Short Circuit, Overload and Over Temperature Protection
- Suitable for use in Emergency Lighting Systems
- Protection Class II
- THD (full load) ≤ 15%
- Ambient Temp -20...+45°C



Code	Output Current [mA]	Min/Max Output [W]	Input Voltage [V]	Output Voltage [V]	Power Factor [λ]	Dimensions L x W x H [mm]
DCC260700-CAS-1325W	260mA	2.6-13W	220-240V~ 50/60Hz	10-50V	0.80C	L124 x W64 x H22.5mm
	> 350mA	3.5-17.5W	220-240V~ 50/60Hz	10-50V	≥0.95	L124 x W64 x H22.5mm
	> 400mA	4-20W	220-240V~ 50/60Hz	10-50V	≥0.95	L124 x W64 x H22.5mm
	> 450mA	4.5-22.5W	220-240V~ 50/60Hz	10-50V	≥0.95	L124 x W64 x H22.5mm
	> 500mA	5-25W	220-240V~ 50/60Hz	10-50V	≥0.95	L124 x W64 x H22.5mm
	> 550mA	5.5-25W	220-240V~ 50/60Hz	10-45V	≥0.95	L124 x W64 x H22.5mm
	> 600mA	6-25W	220-240V~ 50/60Hz	10-42V	≥0.95	L124 x W64 x H22.5mm
	> 700mA	7-25W	220-240V~ 50/60Hz	10-36V	≥0.95	L124 x W64 x H22.5mm

2 channel (Tunable White) version available on indent order. MOQ applies.