SIEMENS

Data sheet

3RW4047-1BB14



SIRIUS soft starter S3 106 A, 55 kW/400 V, 40 $^\circ\text{C}$ 200-480 V AC, 110-230 V AC/DC Screw terminals

| General technical data | | |
|--|----|--------------------------|
| product brand name | | SIRIUS |
| product feature | | |
| integrated bypass contact system | | Yes |
| thyristors | | Yes |
| product function | | |
| intrinsic device protection | | Yes |
| motor overload protection | | Yes |
| evaluation of thermistor motor protection | | No |
| external reset | | Yes |
| adjustable current limitation | | Yes |
| inside-delta circuit | | No |
| product component motor brake output | | No |
| insulation voltage rated value | V | 600 |
| degree of pollution | | 3, acc. to IEC 60947-4-2 |
| reference code according to EN 61346-2 | | Q |
| reference code according to DIN 40719 extended according to IEC 204-2 according to IEC 750 | | G |
| Power Electronics | _ | |
| product designation | | Soft starter |
| operational current | | |
| at 40 °C rated value | А | 106 |
| at 50 °C rated value | А | 98 |
| at 60 °C rated value | А | 90 |
| yielded mechanical performance for 3-phase motors | | |
| ● at 230 V | | |
| - at standard circuit at 40 °C rated value | kW | 30 |
| ● at 400 V | | |
| — at standard circuit at 40 °C rated value | kW | 55 |
| yielded mechanical performance [hp] for 3-phase AC motor at 200/208 V at standard circuit at 50 °C rated value | hp | 30 |
| operating frequency rated value | Hz | 50 60 |
| relative negative tolerance of the operating frequency | % | -10 |
| relative positive tolerance of the operating frequency | % | 10 |
| operating voltage at standard circuit rated value | V | 200 480 |
| relative negative tolerance of the operating voltage at standard circuit | % | -15 |
| relative positive tolerance of the operating voltage at standard circuit | % | 10 |
| minimum load [%] | % | 20 |

| adjustable motor current for motor overload protection minimum rated value | A | 46 |
|--|----|---|
| continuous operating current [% of le] at 40 °C | % | 115 |
| power loss [W] at operational current at 40 °C during operation typical | W | 21 |
| Control circuit/ Control | | |
| type of voltage of the control supply voltage | | AC/DC |
| control supply voltage frequency 1 rated value | Hz | 50 |
| control supply voltage frequency 2 rated value | Hz | 60 |
| relative negative tolerance of the control supply voltage frequency | % | -10 |
| relative positive tolerance of the control supply voltage frequency | % | 10 |
| control supply voltage 1 at AC at 50 Hz | V | 110 230 |
| control supply voltage 1 at AC at 60 Hz | V | 110 230 |
| relative negative tolerance of the control supply voltage at AC at 50 Hz | % | -15 |
| relative positive tolerance of the control supply voltage at AC at 50 Hz | % | 10 |
| relative negative tolerance of the control supply voltage at AC at 60 Hz | % | -15 |
| relative positive tolerance of the control supply voltage at AC at 60 Hz | % | 10 |
| control supply voltage 1 at DC | V | 110 230 |
| relative negative tolerance of the control supply voltage at DC | % | -15 |
| relative positive tolerance of the control supply voltage at DC | % | 10 |
| display version for fault signal | | red |
| Mechanical data | - | |
| size of engine control device | _ | S3 |
| width | mm | 70 |
| height | mm | 170 |
| depth | mm | 190 |
| fastening method | _ | screw and snap-on mounting |
| mounting position | | With additional fan: With vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back Without additional fan: With vertical mounting surface +/-10° rotatable, with vertical mounting surface +/- 10° t |
| required spacing with side-by-side mounting | | |
| • upwards | mm | 60 |
| • at the side | mm | 30 |
| downwards | mm | 40 |
| wire length maximum | m | 300 |
| number of poles for main current circuit | | 3 |
| Connections/ Terminals | | |
| type of electrical connection | | |
| for main current circuit | | screw-type terminals |
| for auxiliary and control circuit | | screw-type terminals |
| number of NC contacts for auxiliary contacts | | 0 |
| number of NO contacts for auxiliary contacts | | 2 |
| number of CO contacts for auxiliary contacts | | 1 |
| type of connectable conductor cross-sections for main contacts for box terminal using the front clamping point | | |
| • solid | | 2x (2.5 16 mm²) |
| finely stranded with core end processing | | 2.5 35 mm ² |
| stranded | | 4 70 mm² |
| type of connectable conductor cross-sections for main contacts for box terminal using the back clamping point | | |
| • solid | | 2x (2.5 16 mm²) |
| finely stranded with core end processing | | 2.5 50 mm ² |

| I | | 10 70 mm² | | |
|--|--|--|--|---|
| tions for | | | | |
| n clamping | | | | |
| | | 2x (2.5 16 r | nm²) | |
| ng | | 2x (2.5 35 r | mm²) | |
| | | 2x (10 50 n | nm²) | |
| tions at AWG | | | | |
| | | 2x (10 1/0) | | |
| | | 2x (10 1/0) | | |
| | | 10 2/0 | | |
| ions for DIN | | | | |
| | | | | |
| | | 2x (10 70 n | nm²) | |
| ions for | | | | |
| | | | · · | |
| | | 2x (0.5 1.5 | mm²) | |
| ions at AWG | | | | |
| | | 2x (7 1/0) | | |
| | | · · · · · | | |
| th core end | | 2x (20 16) | | |
| | | | | |
| vel | m | 5 000 | | |
| | | | | |
| 21 | | 2K2, 2C1, 2S | 1, 2M2 (max. fall height | 0.3 m) |
| | | | | |
| 21 | | 3K6 (no forma | ation of ice, no condensa | ation), 3C3 (no salt |
| | | (30 | and must not get into the | 2011000), 01110 |
| | °C | -25 +60 | | |
| | °C | -40 +80 | | |
| | °C | 40 | | |
| to IEC | | IP20 | | |
| DIEC 60529 | | finger-safe, fo | r vertical contact from th | ne front |
| | | | | |
| | | | | EMC |
| | | - | | • |
| (m) | | Ē | 107 | |
| | | | гпі | <u>v</u> |
| \sim | | \sim | LIIL | |
| | | UL | LUL | RCM |
| ccc | | UL | LIIL | RCM |
| | | UL | LIIL | RCM |
| Ccc Test Certifica | ites | UL | Marine / Shipping | RCM |
| | | UL | Marine / Shipping | RCM |
| Test Certifica Special Test Certifica | | UL <u>Type Test Certific-</u> <u>ates/Test Report</u> | Marine / Shipping | RCM |
| Special Test Ce | | | Lloyd's Register | RCM |
| Special Test Ce | | | Marine / Shipping | RCM |
| Special Test Ce | | | Lloyd's Register | RCM |
| <u>Special Test Ce</u> ate | | | Lloyd's Register | RCM |
| Special Test Ce | | | Lloyd's Register | RCM |
| | ions at AWG ions for DIN ions for DIN ions for ions at AWG th core end vel 1 1 21 | ions for DIN ions for DIN ions for CIN ions for ions at AWG th core end vel m 1 21 21 ions for ions for ions at AWG ions a | ions for clamping 2x (2.5 16 r 2x (2.5 35 r 2x (10 50 r 2x (10 1/0) 2x (10 1/0) 10 2/0 ions at AWG 2x (10 1/0) 2x (10 1/0) 10 2/0 ions for DIN 2 x (10 50 r 2x (10 70 r 2x (10 70 r 2x (0.5 2.5 2x (0.5 1.5 ions at AWG 2x (0.5 2.5 2x (0.5 1.5 ions at AWG 2x (7 1/0) 2x (20 14) 2x (20 14) 2x (20 16) vel m 5 000 1 2K2, 2C1, 2S 1K6 (only occ 1S2 (sand mu 21 °C -25 +60 °C °C -25 +60 °C °C 40 1 to IEC IP20 | ions for clamping $2x (2.5 \dots 16 \text{ mm}^2)$ log $2x (2.5 \dots 35 \text{ mm}^2)$ loss at AWG $2x (10 \dots 50 \text{ mm}^2)$ ions at AWG $2x (10 \dots 1/0)$ loss for DIN $2x (10 \dots 50 \text{ mm}^2)$ loss for $2x (10 \dots 50 \text{ mm}^2)$ loss for $2x (10 \dots 70 \text{ mm}^2)$ loss for $2x (0.5 \dots 2.5 \text{ mm}^2)$ loss at AWG $2x (20 \dots 1.4)$ loss at AWG $2x (20 \dots 14)$ loss at AWG $2x (20 \dots 16)$ loss at AWG $3x (6 (no formation of ice, no condenszion), 1S2 (sand must not get inside the day 3K6 (no formation of$ |



| UL/CSA ratings | _ | | | |
|--|----|-------------|--|--|
| yielded mechanical performance [hp] for 3-phase AC motor | | | | |
| • at 220/230 V | | | | |
| — at standard circuit at 50 °C rated value | hp | 30 | | |
| • at 460/480 V | | | | |
| - at standard circuit at 50 °C rated value | hp | 75 | | |
| contact rating of auxiliary contacts according to UL | | B300 / R300 | | |
| Further information | | | | |
| Simulation Tool for Soft Starters (STS) | | | | |

https://support.industry.siemens.com/cs/ww/en/view/101494917

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RW4047-1BB14

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RW4047-1BB14

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RW4047-1BB14

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RW4047-1BB14&lang=en









last modified:

1/16/2022 🖸