

Current Transformer (CT) Selection Guide for CATCH Power
CATCH Power offers advanced energy management solutions, including support for 200A and 400A split-core Current Transformers (CTs).

SPECIFICATIONS:

- Purpose-Built for CATCH Control: Our CTs are engineered exclusively for our 6-Channel device.
- Flexibility for Larger Mains: Available in 200A and 400A options.
- Enhanced Efficiency tailored for larger residential properties.



Parameter	200A CT	400A CT
Rated Current	200A	400A
Max Current	220A	440A
Output Signal	33mA	33mA
Frequency	50Hz/60Hz	50Hz/60Hz
Insulation Voltage	3KV	3KV
Operating Temp.	-25C to 55C	-25C to 55C
Cable Diameter Capacity	20mm	36mm