

PG4800Ei

4.8 Kw Petrol Inverter Generator

Features & Accessories:

12V DC cables
 Hour meter
 USB Charger 5V, 1A; 5V, 2.1A
 Plug Spanner
 Rubber foot x 4
 Engine Smart Control
 Battery



**NZ BASED
 BACKUP**



**GREAT FOR
 THE HOME**



Inverter generator producing “clean or pure sine wave” power. It is suitable for use with all tools and appliances.

This model comes with electric start.

GENERATOR

Rated Frequency (Hz)	50
Rated voltage (V)	230
Rated output (kW)	4.2
Maximum output (kW)	4.8
Rated current (A)	18.26
Power factor (φ)	1.0
Phase	Single
DC output	12V/8.3A

ENGINE

Engine type	1 cylinder, 4 stroke, OHV
Displacement (cc)	236 (9hp)
Ignition system	TCI
Spark plug	F6TC, F6RTC
Starting system	Recoil + Electric
Lubricating system	Splashed
Lubricating oil	SAE 10W-30, Synthetic 5W-30
Oil capacity (l)	0.6
Fuel type	91 Unleaded gasoline
Continuous run time @ 50% load (hr)	9.43
Cooling system	Forced Air
Noise level (dB/7m)	74
Fuel tank capacity (l)	15

PACKAGING

Outer carton dimensions (L x W x H mm)	510 x 445 x 520
Machine dimensions (L x W x H mm)	500 x 425 x 500
Net / gross weight (kg)	35 / 37

This specification sheet does not constitute a contract or offer for sale. For the most up-to-date and specific product information, please contact our authorized representatives or visit our website. All product names, logos, and trademarks are the property of their respective owners and are used for identification purposes only.

