

PG9800Ei

9.8 Kw Petrol Inverter Generator

Features & Accessories:

12V DC cables
 Hour meter
 USB Charger 5V, 1A; 5V, 2.1A
 1 x 15A Socket IP66
 1 x 32A Socket IP66
 Engine Smart Control
 Remote Start
 Battery
 Wheels and handles
 Port for automatic transfer switch
 Fully Enclosed Structure



NZ BASED
BACKUP



GREAT FOR
THE HOME



Inverter generator producing “clean or pure sine wave” power. Suitable for use with all tools and appliances.

This generator has maximum output of 9.8KW and has an ATS port for automatic connection to a house or workshop when power fails.

This specification sheet does not constitute a contract or offer for sale. For the most up-to-date and specific product information, please contact our authorized representatives or visit our website. All product names, logos, and trademarks are the property of their respective owners and are used for identification purposes only.

GENERATOR

Rated Frequency (Hz)	50
Rated voltage (V)	230
Rated output (kW)	9.0
Maximum output (kW)	9.8
Rated current (A)	39.1
Power factor (φ)	1.0
Phase	Single
DC output	12V/8.3A

ENGINE

Engine type	1 cylinder, 4 stroke, OHV
Displacement (cc)	485 (20Hp)
Ignition system	TCI
Spark plug	F6TC, F6RTC, BPR6ES
Starting system	Recoil + Electric + Remote
Lubricating system	Splashed
Lubricating oil	SAE 10W-30, Synthetic 5W-30
Oil capacity (l)	1.1
Fuel type	91 Unleaded gasoline
Continuous run time @ 50% load (hr)	11
Cooling system	Forced Air
Noise level (dB/7m)	69
Fuel tank capacity (l)	32

PACKAGING

Outer carton dimensions (L x W x H mm)	865 x 640 x 815
Machine dimensions (L x W x H mm)	815 x 580 x 760
Net / gross weight (kg)	110 / 115

